## Set-up Voicemail

- 1. Pick up the phone receiver
- 2. Hit the messages " ( button
- 3. Enter 124578# at the initial prompt
- 4. Follow the instructions

## Voicemail Set-up Instructions with No Phone

- 1. Dial your site phone number (example—x2-#### {788-####})
- 2. Press # when you hear the recording
- Enter your Personal Extension, then # (example—<u>82819#</u> {your personal phone extension & #})
- 4. Enter the default Password 124578#
- 5. Follow the Instructions

## Locked Voicemail Account

- 1. Call Help Desk at VOIP Extension, x81099
- 2. Ask for assistance with your locked voicemail account

## **3 Ways to Retrieve Voicemail**

- 1. To log on from your extension:
  - Press " 💌 " or "**Messages**" button
  - Enter ID (your 5-digit extension), press "#"
  - Enter password
- 2. To log on from outside the system:
  - Dial voicemail pilot number **951-328-4000**
  - Or, your direct number. Press "\*"
  - Enter ID (your 5-digit extension), press "#"
  - Enter password
- 3. To log on from your Outlook:
  - Open message with attachment—From: Unity Messaging
  - Open message with attachment—From: RUSD Caller ID Name